

| Model | Portable Power Station 1280W Specifcation |
|-----------------------------|---|
| Dimensions | 300*195*290MM |
| Net weight | 12kg |
| Material | Fireproof ABS |
| Battery | Rated voltage: 25.6V 50Ah |
| | Battery Capacity :400000mAh |
| | Battery power: 1280Wh |
| | Battery type: LiFePO4 |
| Charging input | DC in: 24V 7.5A DC6.3*3.0 |
| | Type-C PD100W 5V3A 9V3A 12V3A 15V3A 20V5A |
| | DC input:8.5h PD input:15h DC+PD input:5.5h |
| | solar charge :MPPT 12-25V (180W max.) |
| | car charge : 12V 5A 60W |
| USB output | USB1 : QC3.0 / BC1.2 /5V3A 9V2A 12V 1.5A |
| | USB2 : QC3.0 / BC1.2 /5V3A 9V2A 12V 1.5A |
| | Type-C 1 : PD100W 5V3A 9V3A 12V3A 15V3A 20V5A |
| | Type-C 2 : PD18W QC3.0 |
| DC output | DC5.5*2.1 *2 |
| | Cigarette Lighter Socket*1 12V 10A (MAX) |
| AC output | Voltage: 220V / 110V |
| | Frequency 50HZ/60HZ can be set manually |
| | AC output*3 |
| | Rated power: 1200W Peak power: 2400W |
| Display Screen | white nixie tube display |
| | Display content: percentage battery, charging input/output state, power |
| LED light | 6W LED light |
| | Red-Yellow warning light |
| Button | Power on/off |
| | AC on/off |
| | DC on/off |
| | USB on/off |
| | Lighting : turn on/off the light, adjust brightness, light mode |
| Fan | 2*cooling fan |
| Working temperature | -20℃~65℃ |
| Charging temperature | 0℃~60℃ |